

# ELECTRONS SOURCES WITH WHISKER FIELD EMITTERS, AND METHOD OF MANUFACTURING

## BACKGROUND OF THE INVENTION

### FIELD OF THE INVENTION

This invention relates to microelectronics, including vacuum microelectronics, in particular to field emission devices, specifically to field emission cathodes, as well as to other field emission devices such as field emission displays, electron sources for electron guns, for microwave devices, etc.

### DESCRIPTION OF THE RELATED TECHNOLOGY

During the last few years, various versions for realization of field emission, including the emission with using of defects in planar structures, have been considered, the defects acting as initiators of the field emission [1,2]. Field emitters such as tips and blades prepared by special methods, as field emission initiators, have many advantages in comparison with the defects from the point of view of feasibility to realize regular multiple arrays of the field emitters and controlled growing of the arrays on large areas. However, cases often occur at the practice when the regular arrays are inferior to structures with an incidental distribution of the defects in homogeneity.

Troubles in stability and controllability of electron flows given off by the field emitters are also known. Troubles with uniformity of the field electron emission of the multiple field emitter arrays are of the same nature. The uniformity is typically ensured by ballast resistors that equalize electron currents through different field emitters of the multiple field emitter arrays.

Various design and technological solutions are used for overcoming of the troubles (problems) with the field emitter.

A controlled electron source is known where the field emitter is connected to the drain of MOSFET that serves as a stable current electron source [3,4]. In such an electron source, the issue of stability and controllability of the field emission current is successfully solved. However, transistor p-n junctions in the electron source are placed in the substrate where the field emitter is placed, too, and a substrate, too. This increases significantly the area taken by a

pixel and, accordingly, decreases the resolving power of field emission displays based on such electron sources.

A solution of the problems of stability and controllability combined with the spatial arrangement of the control components is successfully realized in the patent [5]. Here, in the electron source a diode is placed in the emitter base for the stability and the controllability of the field emission current. Such a design decreases principally the sizes of the electron source three times, as minimum, because its control component takes the same place as the field emitter itself. Such an electron source allows to regulate the voltage so that the starting voltage for the field emission is decreased and, in such a way, the uniform emission is ensured. A plurality of emitters, acting through diodes and operating actually as ballast resistors, are placed onto the cathode electrode. Such a design ensures the uniformity of the field emission and, simultaneously, its controllability. However, the proposed in [5] components of stabilization and control of the field emission current are insufficient for successful solving of the problems of uniformity and controllability.

In the patent [6] a more complete using of the advantages of the field emitters is realized. The field emitter is considered as a spatially distributed object (various parts of which serve as functional components of a device) rather than as a "material point" of the field emission, without spatial characteristics of their various parts.

According to the patent [6] components for control of the electron source are transformed from the planar arrangements, as it was done in [3,4], into a vertical arrangement. Thus, a principal role in the stabilization and control of the field emission current is assigned (allocated), to the body and to the surface of the field emitter, in addition to the usual role of its top.

Similar to [3-5] in the patent [6] an extracting electrode acts to electrons placed in the emitter top. In [6] electron sources are considered where the field emitters have sufficient length and thickness. Therefore, from the point of the action of the control electrodes or barriers (such as the diode in [5]), as minimum four areas of the electron sources are considered: -the substrate on which the field emitter is placed; -the basis of the field emitters; -the top of the field emitters; -their bodies.

These are areas of selective activation, or active areas.

So, the active area is an area in the substrate, in body of the field emitter, in its basis or at its top. A connection of the source of the charge carriers with the field emitter is implemented

through the areas, and a control of the field emission current (of the charge carriers flow) from one area to another by means of stimulation and extracting is implemented.

In some cases, however, such a control of the charge carrier flow can not be realized in [6]. This is related to the fact that the field emitter, being under the action of a rather high electric field, for example, of the anode one, is subjected to its influence not only to the area of the top of field emitter but also all over the body. As a result, such an electric field, acting to the field emitter, "shorts out" an action various barriers and over control components. The method for preparation of the field emitters by "wet" or "dry" etching used in the patent [6] results in formation of the emitters having small ratios of the length  $l$  of the active area to its diameter  $d$ . In this case, for controlling of the field emission current, a very large voltage must be used in order to compensate the action of the large external (for example, of anode) electric field.

Indeed, if the field emitter, containing a part with the p-type conductivity is placed in the electric field  $E$  (Fig. 3C), formed by the anode, the boundary of the first of the first p-n junction 04 is shifted  $E_j$  to the p-area. At a certain value  $E_i$ , the first junction 04 approaches to the second one 06 in such an extent that the electrons from the n-area  $c$  begin tunneling through the narrowed barrier to the field emitter. This causes emission of electrons from field emitter. This is the "shorting out" under the external electric field. Existence of the control electrode near the field emitter both in traditional (Fig. 3A) and in the considered [6] version (Fig. 3B) can compensate the action of the penetrating electric field and, such a manner, to "lock" the charge carriers of the second n-area  $c$ . However, it is known that, at the geometric sizes, considered in [6], the length  $l$  of the p-area is compatible with or and even shorter than the width  $d$ . As it is known, for "locking" of the charge carriers value of the traverse electric field of the control electrode 02 or 08 must be comparable with the longitudinal field responsible for the charge carrier flow. This makes it necessary to apply large voltages to the control electrodes.

In addition, in the patent [6] the control electrodes stimulate the flowing of the charge carriers through the active area and extract the electrons from the field emitter. In such a way, the electron emission is stabilized and controlled. At the same time the control electrodes in [6] does not lock the flow of the charge carriers through the active area. The above function of the control electrodes-to stimulate the flowing of the charge carriers, makes it necessary mentioned in [6] approximate sizes of p-area as "... formed to no more than several microns in thickness and generally to submicron order thickness" (see column 8, last paragraph in [6]). This means that

the authors of [6] did not consider a possibility to provide the control electrode by "locking" function and, as a result, they considered the design which is enough just for stimulation and which is not enough for locking the electrons moves under the influence of strong external electric field. However, it is known that if the control electrodes can lock the flow, it is possible to use small (in absolute value) negative voltage for the locking of the flow. This approach is very important from practical point of view-to use low voltage "electric keys" in different driving systems, for example, in the field emission displays. Such a version can not be realized in [6] due to small value of the characteristic  $l/d$  that is there approximately equal to 1 which is provided by the design proposed in [6].

In this invention, the drawback is overcome owing to the fact that. here, for stabilization and controlling of the field emission, a whisker ("filament crystal") characterized by  $l/d \gg 1$  is used. A method for preparation of the whiskers with traverse p-n junctions is also proposed in this invention. As a result, the design proposed allows to control the field emission by locking the charge carrier flow.

The approach proposed is especially important at creation of effective long-living flat panel displays. Indeed, the higher the anode (accelerating) electric field, the more effective and long-living are their phosphors because, the efficiency is larger at higher voltages. Also at the increasing of anode voltage in such devices and, accordingly, decreasing of the current the durability of the phosphors is increased. The high accelerating voltage allows to use a protecting coating layer (for example, aluminum) that prevents the decomposition of the phosphors and increases the illumination owing to the light reflection. In addition. the decreasing currents are useful for the field emitters themselves (especially of semiconductor emitters) because at high currents the emitters are heated resulting in their degradation.

*Sub. cl 7* In this invention various possibilities for the stabilization and control of the field emission current based on using of epitaxially grown whiskers are proposed. By whisker growing, the ratio  $Vd$  can be implemented as 5-10 and more times. In addition, with the whisker grown field emitters broad possibility for shape variation and creation of the control electrodes can be realized. In particular, a design with step-shaped emitter is proposed Fig. 4c.

According to this invention, the field emitter is implemented of whisker that includes at least one barrier (for example, n, n+, p, p+ or p-n junction), i.e., the barrier is placed in the body of the field emitter, being at some height  $h > 0$  (Fig. 4a) above the substrate, i.e., above its own

basis. At the same time in the patents [3,5] one of the barrier is placed at the basis of the field emitter being either at the upper level of the substrate or below it.

As it was mentioned above the active area can be placed both in the basis of field emitter [5], top [3,5] or substrate [3], and in the body of the field emitter [6]. In this invention a version is proposed when the active area is placed on side surface of the field emitter or in the body of the material that has direct or indirect contact with substrate or field emitter.

The active area can be placed also in thin surface conductive layer arranged on an insulating substrate. Thus, the version of the controlling electron source as purposed in this invention not only has solved the problem of transferring the stabilizing and controlling components from their planar arrangement to vertical one (and, in such a way, of increasing the resolution of the device) but also allows to conserve the controllability of the emission current by means of low voltage. In such a way, this allows to realize said controllability both in the case of low and high external electric field.

In the patent [6], as it was mentioned above, the method for fabrication of the field emitters with traverse p-n junctions. However, this method does not allow to obtain optimal geometric parameters of the field emitter that gives necessary functional characteristics.

The methods for growing oriented whiskers arrays are known [7,8,9,10]. The methods, however, do not contain procedures for preparation of the junction, for example, like p-n junctions. In this invention, such procedures are proposed.

## SUMMARY OF THE INVENTION

An electron source is proposed, the source including a field emitter, a substrate, a source of charge carriers, and at least one ballast resistor. The field emitter is implemented of a whisker epitaxially grown on the substrate, and at least one ballast resistor is implemented as a barrier which is represented as a boundary in the body of the field emitter. The boundary is formed by a contact of materials with different kinds of conductivity.

In the electron source the field emitter is implemented of at least one semiconductor material. At least one barrier in the electron source is formed by junction of materials with different kinds of conductivity, such as n, n<sup>+</sup>, p, p<sup>+</sup> kinds. At least one barrier is formed by an insulating layer that is across to direction of charge carriers flow.

The field emitter is formed by a tip, the tip consisting of two coaxial parts, a broad lower part and a narrower upper part. The field emitter can be also formed by a blade. The tops of the field emitter are sharpened and coated by diamond or diamond-like material, and the coatings can be sharpened, too.

At another version of the electron source the barrier is formed by a boundary between a body of the field emitter and a conducting layer placed on a surface of the field emitter. In the electron source, at least one ballast resistor is implemented as a barrier which is represented as a boundary in the field emitter body, the boundary being formed by contacts of the materials with different kinds of conductivity.

The field emitter is implemented of at least one semiconductor material, and the conducting layer is also implemented of at least one semiconductor material.

At least one barrier in the field emitter is formed by junction of materials with different kinds of conductivity, such as n, n<sup>+</sup>, p, p<sup>+</sup> kinds.

In another version of the electron source at least one barrier is formed by an insulating layer that is across to the direction of charge carriers flow.

The field emitter can be formed either by a tip or by a blade. In the case of the tip shape the field emitter consists of two coaxial parts, a broad lower part and a narrower upper part. The top of the field emitter is sharpened and coated by diamond or diamond-like material, the coating being sharpened, too.

The source of the charge carriers is connected to the field emitter via substrate and/or a conducting layer placed on a surface of the field emitter directly or via an insulating layer.

In one more version of the electron source the substrate has a shape of a tip and is formed by an insulator and by a conductive layer, the ballast resistor being implemented by the layer.

The conductive layer in the electron source contains at least one barrier for charge carriers. At least one barrier in the electron source is formed by junction of materials with different kinds of conductivity, such as n, n<sup>+</sup>, p, p<sup>+</sup> kinds, and at least one barrier is formed by insulating layer that is across to direction of charge carriers flow.

In one more version the electron source can be controlled containing at least one control electrode. The electron source can contain at least one active area in the body and/or on the surface of the field emitter. The active area can be realized in conducting layer placed on the surface of the substrate and/or of the field emitter directly or via an insulator layer.

At least one control electrode is placed close to one barrier for the charge carriers or on side surface of the field emitter via an insulator layer. The control electrode is separated from the field emitter by a vacuum gap or placed along the field emitter. The control electrode can have a direct contact with the side surface of the field emitter.

The substrate in the controlled electron source can be crystalline, or can be implemented by an insulator and a conductive layer placed on the insulator. The substrate can be implemented of the single-crystalline material with orientation (111).

The surface of the substrate can be coated by a material which is transparent for electrons and which prevents outlet of chemical elements from the surface of the controlled electron source, the material being diamond or diamond-like carbon.

The invention also considers a matrix of the controlled electron sources containing at least two controlled electron sources. The matrix can contain a two-dimensional system of mutually perpendicular rows of the controlled electron sources, at least one of the control electrode of the electron sources having a diaphragm shape and being implemented of diamond or diamond-like material.

The substrate on which the controlled electron source is arranged is implemented of conductive material placed on an insulator.

The matrix contains conductive buses which form two systems where buses of each of the systems are mutually parallel whereas the buses of two different systems are mutually perpendicular, the two systems being placed in two levels and separated by an insulating layer.

This invention proposes also a method for preparation of controlled electron sources including a formation on a solid substrate of field emitters each of that contains at least one transverse junction formed by materials having different electrical conductivity, a formation of at least one controlled electrode close to such junctions, where the field emitters are implemented of whiskers epitaxially grown by the vapor-liquid-solid mechanism. The implementation of the field emitters can include formation of the hollows in the substrate and deposition of solvent particles at the bottom of the hollows. The implementation of the field emitters can also include placing of solvent particles on the substrate and etching of the substrate around the particles.

As mentioned above, the method can include further procedure for formation of the field emitters, that is to say, placing of a source material, having a first kind of conductivity, opposite to the substrate with the solvent particles on it, growing of whiskers having the first kind of

conductivity, stabilized cooling of the grown whiskers, having the globules on its tops, with an introduction of an inert gas into atmosphere, with simultaneous decreasing of the temperature of the substrate, changing of the source material for another source having a second kind of conductivity, stabilized heating of the grown whiskers, having the globules on its tops, with an introduction of an inert gas into atmosphere, with simultaneous increasing of the temperature of the substrate, and growing of whiskers having the second kind of conductivity. The method also includes possibility to change the source materials more than two times.

As mentioned above, the method can also include further procedure for formation of the field emitters includes growing of whiskers in a gaseous atmosphere containing the element or elements of which the substrate consists, introduction of doping gaseous compounds into the gas atmosphere. According to the method the formation of the field emitters can include more than one procedure of introduction into the gas atmosphere of different gaseous doping compounds.

#### BRIEF DESCRIPTION OF DRAWINGS

Fig. 1. Illustration of the field emission cathode according to the prior art [5].

1-substrate ; 2-cathode; 3-diode ; 4-metallic layer; 5-semiconductor layer; 6-emitter ; 7 - insulating layer; 8-control electrode.

Fig. 2a, 2b. Illustrations of the field emission devices according to the prior art [3].

Fig. 3a. 3b. Illustrations of the field emission devices according to the prior art [6]. 01-top of (whisker grown) field emitter : 02-control 06-barrier (p-n junction) : 08-control electrode : 09-conductive part of substrate : 09i-insulator part of substrate; a, b, c-areas of various conductivity kinds; e-position of active areas.

Fig 3c. Illustration of the field emitter with various function areas of the prior art. E-external electric field; E<sub>j</sub>-various positions of junction boundary (for example, p-n) under the influence of external electric fields of various value; E<sub>e</sub>-position of junction boundary when electrons start to flow through junction : i-length of the active area : d-width of the active area.

Fig. 3d. Illustration of the method for preparation of the field emitter according to [6]. 12,13,14-layers with different kinds of conductivity.

Fig. 4a, 4b, 4c, 4d, 4e. Illustrations of the stabilized electron sources according to the present invention. q-possible movement of charge carriers; h-height of the position of the barrier



above the substrate; 03-insulator if charge carriers are provided via surface layer; 03-conductive material if charge carriers are provided via substrate.

Fig. 5a, 5b, 5c, 5d. Illustrations of the controlled electron sources according to the present invention

Fig. 6a. Illustration of the matrix system of the controlled electron sources according to the present invention. 07-aperture. Rows of control electrodes 02 and 08 are mutually perpendicular, and together realize the controlling of the emission of the matrix system.

Fig. 6b. Illustration of the matrix system of the controlled electron sources according to the present invention. Rows of control electrodes 02 and rows of conductive part 09 of substrate based on insulate part 09i of the substrate are mutually perpendicular, and together realize the controlling of the emission of the matrix system.

Fig. 7. Illustration of grown silicon whisker with transversal barriers (junctions) 15-solidified globule consisting of crystallites of silicon and solvent; by acting to the whisker with a chemical etch of silicon, the whisker is transformed into tip with simultaneous removal of the globule.

#### DETAILED DESCRIPTION OF THE INVENTION.

EXAMPLE 1. A most typical version for realization of the stabilized electron sources that uses a barrier as a ballast resistor is the following. A thin layer of n-type silicon is deposited onto p-type silicon tip that epitaxial to substrate (Fig. 4d). The junction between the p-type of silicon and then-type silicon coating acts as a ballast resistor.

EXAMPLE 2. A most typical version for realization of the controlled electron sources that uses a vertical arrangement of the control components is the following. The tip contains in its body two p-n junctions. An upper part of the tip is implemented of n-type material. A lower part of the tip as well as the adjacent substrate are implemented of n-type material. A control electrode is placed at a middle part of the tip which is implemented of p-type material. The control electrode has an extended length, is placed on the surface of the tip and has with it a direct contact (Fig. 5c). When a voltage VOPD is applied to the control electrode, an inverse layer is induced at the area b along the surface of the field emitter, and electrons from the area c begin to penetrate into area a through the inverse layer. Then the electrons are emitting from the field emitters under the action of the anode voltage.

EXAMPLE 3. A most typical version for realization of the matrix system of the controlled electron sources that uses the vertical arrangement of the control components is the following.

Rows of sharpened whisker-grown field emitters 01 are formed on a conducting substrate 09' of silicon having the crystallographic orientation (111), see Fig. 6a. A system of parallel rows of control electrodes 08 is formed on the surface of the field emitters, the insulating layers 03 being placed between the field emitters and the control electrodes. Then, an insulating glass layer 03' is deposited on the structure. After that, a set of parallel stripes 02 are deposited onto the glass, and centrosymmetrical cavities 07 are formed at the places corresponding to the emitters so that the upper ("top") of each of the emitters are in the centers of the cavities being risen above their bottoms. It is important that the set of the stripes 02 is perpendicular to the system of parallel rows of the control electrode 08. In order to obtain an emission from a given field emitter, it is necessary to apply a voltage  $V_{open}$  to a row in the system of the control electrodes 08 and, simultaneously, to apply a voltage  $V_{ext}$ , to a stripe in the set 02. At the cross of the row and of the stripe, the sum voltage  $V_{open} + V_{ext}$ , initiates the emission.

## REFERENCES

1. I. Brodie, P. R. Schwoebel, Vacuum Microelectronic Devices, Proceedings of the IEEE. Vol. 82, No. 7, July 1994
2. W. Zhu, G. P. Kochanski, S. Jin and L. Siebles, J. Appl. Phys. 78 (1995) 2707
3. H. F. Gray, Regulatable field emitter device and method of production thereof US Pat. 5,359,256, CI 313/169 (1994).
4. Junji Itoh, Takayuki Hirano, and Seigo Kanemaru, Ultrastable emission from a metaloxide-semiconductor field-effect transistor-structured Si emitter tip, Appl. Phys. Lett. 69 (11), 9 September 1996, p. 1577
5. Yoichi Kobori, Mitsuru Tanaka, Field emission cathode, US Pat. 5,162,704, CI 315/349 (1992).
6. Seigo Kanemaru, Junji Itoh, Field emitter having source, channel, and drain layers, US Patent 5,710,478, Date of patent 20.01.1998
7. E. I. Givargizov, Method and apparatus for growing oriented whisker arrays, RU Patent 2,099,808, 20.12.1997r.
8. Yoshinori Terui, Ryuichi Terasaki, Method for producing single crystal, and needle-like single crystal, US Patent # 5,544,617 Date of patent 13.08.1996
9. Didier Pribat et al, Method for the controlled growth of crystal whiskers and application thereof to the making of tip microcathodes.
10. Michio Okajima et al, Fabrication method of fine structures, US Patent 5,381,753 Date of patent 17.01.1995